

Rec'd PCT/PTO 04 APR 2002

TRANSMITTAL LETTER TO THE UNITED STATES DESIGNATED / ELECTED OFFICE (DO/EO/US) CONCERNING A FILING UNDER 35 U.S.C. 371		ATTORNEY'S DOCKET NUMBER P67724US0
		US APPLICATION NO (If known, see 37 CFR 1.5) 10/089060
INTERNATIONAL APPLICATION NO PCT/SE00/01933	INTERNATIONAL FILING DATE 4 October 2000	PRIORITY DATE CLAIMED 4 October 1999
TITLE OF INVENTION ANTENNA MEANS		
APPLICANT(S) FOR DO/EO/US Mattias HELLGREN and Lars CARLSSON		

Applicant herein submits to the United States Designated/Elected Office (DO/EO/US) the following items and other information.

1. ☒ This is a **FIRST** submission of items concerning a filing under 35 U.S.C. 371.
2. ☐ This is a **SECOND** or **SUBSEQUENT** submission of items concerning a filing under 35 U.S.C. 371.
3. ☒ This express request to begin national examination procedures (35 U.S.C. 371(f)) at any time rather than delay examination until the expiration of the applicable time limit set in 35 U.S.C. 371(b) and PCT Articles 22 and 39(1).
4. ☒ A proper Demand for Internatl. Preliminary Examination was made by the 19th month from earliest claimed priority date.
5. ☒ A copy of the International Application as filed (35 U.S.C. 371(c)(2))
 - a. ☒ is transmitted herewith (required only if not transmitted by the International Bureau).
 - b. ☒ has been transmitted by the International Bureau.
 - c. ☐ is not required, as the application was filed in the United States Receiving Office (RO/US)
6. ☐ A translation of the International Application into English (35 U.S.C. 371(c)(2)).
7. ☒ Amendments to the claims of the International Application under PCT Article 19 (35 U.S.C. 371(c)(3))
 - a. ☐ are transmitted herewith (required only if not transmitted by the International Bureau).
 - b. ☐ have been transmitted by the International Bureau.
 - c. ☐ have not been made; however, the time limit for making such amendments has NOT expired.
 - d. ☒ have not been made and will not be made.
8. ☐ A translation of the amendments to the claims under PCT Article 19 (35 U.S.C. 371(c)(3)).
9. ☐ An oath or declaration of the inventor(s) (35 U.S.C. 371(c)(4)).
10. ☐ A translation of the annexes to the Internatl. Preliminary Examination report under PCT Article 36 (35 U.S.C. 371(c)(5)).

Items 11. to 16. below concern other document(s) or information included:

11. ☐ An Information Disclosure Statement under 37 CFR 1.97 and 1.98.
12. ☐ An assignment document for recording. A separate cover sheet compliance with 37 CFR 3.28 and 3.31 is included.
13. ☒ A **FIRST** preliminary amendment.
☐ A **SECOND** or **SUBSEQUENT** preliminary amendment.
14. ☐ A substitute specification.
15. ☐ A change of power of attorney and/or address letter.
16. ☒ Other items or information:

International Search Report
 First Page of Publication
 International Preliminary Examination Report - with no annexes

US APPLICATION NO (if known, see 37 CFR 1.5) 10/089060		INTERNATIONAL APPLICATION NO. PCT/SE00/01933		ATTORNEY'S DOCKET NUMBER P67724US0	
--	--	--	--	--	--

<p>17. <input checked="" type="checkbox"/> The following fees are submitted:</p> <p>Basic National Fee (37 CFR 1.492(a)(1)-(5)):</p> <p>Internatl. prelim. examination fee paid to USPTO (37 CFR 1.492 (a) (1)) .. \$710.00</p> <p>No international preliminary examination fee paid to USPTO (37 CFR 1.492 (a) (2)) but international search fee paid to USPTO (37 CFR 1.445(a)(2)) .. \$740.00</p> <p>Neither international preliminary examination fee (37 CFR 1.492 (a) (3)) nor international search fee (37 CFR 1.445(a)(2)) paid to USPTO) \$1040.00</p> <p>International preliminary examination fee paid to USPTO (37 CFR 1.492 (a) (4)) and all claims satisfied provisions of PCT Article 33(2)-(4) \$100.00</p> <p>Search Report prepared by the EPO or JPO (37 CFR 1.492 (a) (5)) \$890.00</p> <p style="text-align: right;">ENTER APPROPRIATE BASIC FEE AMOUNT =</p>				CALCULATIONS		PTO USE ONLY	
				<p>\$ 1040.00</p>			

<p>Surcharge of \$130.00 for furnishing the oath or declaration later than <input type="checkbox"/> 20 <input checked="" type="checkbox"/> 30 months from the earliest claimed priority date (37 CFR 1.492(e)).</p>				\$ 130.00			
--	--	--	--	-----------	--	--	--

Claims	Number Filed	Number Extra	Rate			
Total Claims	16 - 20 =	-0-	x \$18.00	\$		
Independent Claims	1 - 3 =	-0-	x \$84.00	\$		
Multiple Dependent Claim(s) (if applicable)			+ \$280.00	\$		
TOTAL OF ABOVE CALCULATIONS =				\$ 1170.00		

<p>Reduction by 1/2 for filing by small entity, if applicable. Verified Small Entity statement must also be filed. (Note 37 CFR 1.9, 1.27, 1.28).</p>				\$			
SUBTOTAL =				\$ 1170.00			

<p>Processing fee of \$130 for furnishing the English translation later than <input type="checkbox"/> 20 <input type="checkbox"/> 30 months from the earliest claimed priority date (37 CFR 1.492(f))</p>				\$			
TOTAL NATIONAL FEE =				\$ 1170.00			

<p>Fee of \$40.00 for recording the enclosed assignment (37 CFR 1.21(h)). Assignment must be accompanied by appropriate cover sheet (37 CFR 3.28, 3.31).</p>				\$			
TOTAL FEES ENCLOSED =				\$ 1170.00			

				Amt. to be refunded:		\$	
				Amt. charged:		\$	


a. ☒ A check in the amount of \$ 1170.00 to cover the above fees is enclosed.

b. ☐ Please charge my Deposit Account No. 06-1358 in the amount of \$ _____ to cover the above fees. A duplicate copy of this sheet is enclosed.

c. ☒ The Commissioner is hereby authorized to charge my account any additional fees set forth in §1.492 during the pendency of this application, or credit any overpayment to Deposit Account No. 06-1358. A duplicate copy of this sheet is enclosed.

SEND ALL CORRESPONDENCE TO:

JACOBSON HOLMAN PLLC
400 7th Street, N.W., Suite 600
Washington, DC 20004
202-638-6666
CUSTOMER NUMBER: 00136

By 
John C. Holman
Reg. No. 22,769

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applicants: Mattias HELLGREN et al.

Serial No.: New

Filing Date: April 4, 2002

For: ANTENNA MEANS

PRELIMINARY AMENDMENT

Commissioner for Patents
Washington, D.C. 20231

Sir:

Prior to initial examination, please amend the above-identified application as follows:

IN THE SPECIFICATION

On page 1, immediately following the title, please insert the following sentence: --This is a nationalization of PCT/SE00/01933 filed October 4, 2000 and published in English.--

IN THE CLAIMS

Please amend claims 3, 4, 5, 7, 8, 11 & 13-16 as follows:

3. (amended) The antenna means according to claim 1, characterised in that said conductive radiating structure (10) having a total length of $\lambda/4 - \lambda$ at a frequency in the frequency band to be received and/or transmitted by the antenna.

4. (amended) The antenna means according to claim 1, characterised

in that said conductive radiating structure (10) being a flexible film attached to a dielectric substrate.

5. (amended) The antenna means according to claim 1, characterised in that said conductive radiating structure (10) exhibits at least a planar section, said planar section is forming an angle (α) with said ground plane means, where (α) is in the range of 30-150°.

7. (amended) The antenna means according to claim 1, characterised in that said conductive radiating structure (10) being meander shaped.

8. (amended) The antenna means according to claim 1, characterised in that it further comprises a tuning/matching means (16) for tuning/matching to one or multiple frequencies.

11. (amended) The antenna means according to claim 1, characterised in that it further comprises at least one bridge connector (18) being an electrical conductor with a first end and a second end, each connected to different parts of said at least one elongated open loop.

13. (amended) The antenna means according to claim 11, characterised in that said tuning/matching means (16) is arranged close to said bridge connector (18) for forming a capacitive and inductive coupling therebetween.

14. (amended) The antenna means according to claim 11, characterised in that said bridge connector (18) is meander shaped.

15. (amended) The antenna means according to claim 1, characterised in that the first end of the conductive radiating structure (10) is coupled to ground.

16. (amended) An antenna assembly including an antenna means (1) according to claim 1, wherein the assembly comprises at least one further antenna element for transmitting/receiving radio frequency signals, for instance, a GPS antenna.

REMARKS

The foregoing Preliminary Amendment is requested in order to delete the multiple dependent claims and avoid paying the multiple dependent claims fee.


Attached hereto is a marked-up version of the changes made to the specification and claims by the current amendment. The attached page is captioned "**VERSION WITH MARKINGS TO SHOW CHANGES MADE.**"

Early action on the merits is respectfully requested.

Respectfully submitted,

JACOBSON HOLMAN PLLC

By _____


John C. Holman
Reg. No. 22,769

400 Seventh Street, N.W.
Washington, D.C. 20004-2201
(202) 638-6666

Atty. Docket: P67724US0
Date: April 4, 2002
JCH/cmf

VERSION WITH MARKINGS TO SHOW CHANGES MADEIN THE CLAIMS

3. (amended) The antenna means according to claim 1 [or 2], characterised in that said conductive radiating structure (10) having a total length of $\lambda/4$ - λ at a frequency in the frequency band to be received and/or transmitted by the antenna.

4. (amended) The antenna means according to claim 1 [any of the claims 1-3], characterised in that said conductive radiating structure (10) being a flexible film attached to a dielectric substrate.

5. (amended) The antenna means according to claim 1 [any of the claims 1-4], characterised in that said conductive radiating structure (10) exhibits at least a planar section, said planar section is forming an angle (α) with said ground plane means, where (α) is in the range of 30-150°.

7. (amended) The antenna means according to claim 1 [any of the preceding claims], characterised in that said conductive radiating structure (10) being meander shaped.

8. (amended) The antenna means according to claim 1 [any of the preceding claims], characterised in that it further comprises a tuning/matching means (16) for tuning/matching to one or multiple frequencies.

11. (amended) The antenna means according to claim 1 [any of the

preceding claims], characterised in that it further comprises at least one bridge connector (18) being an electrical conductor with a first end and a second end, each connected to different parts of said at least one elongated open loop.

13. (amended) The antenna means according to claim 11 [or 12], characterised in that said tuning/matching means (16) is arranged close to said bridge connector (18) for forming a capacitive and inductive coupling therebetween.

14. (amended) The antenna means according to claim 11[-13], characterised in that said bridge connector (18) is meander shaped.

15. (amended) The antenna means according to claim 1 [any of the preceding claims], characterised in that the first end of the conductive radiating structure (10) is coupled to ground.

16. (amended) An antenna assembly including an antenna means (1) according to claim 1 [any preceding claim], wherein the assembly comprises at least one further antenna element for transmitting/receiving radio frequency signals, for instance, a GPS antenna.

ANTENNA MEANS**FIELD OF THE INVENTION**

The present invention relates to an antenna means in general and specifically to an antenna means for transceiving RF signals in at least a first frequency band.

DESCRIPTION OF THE RELATED ART

With the recent rapid progress of electronic communication technique, communication apparatuses having a higher function and smaller size have been developed and utilised for various kinds of mobile communication apparatuses.

Antenna means transmitting and receiving (transceiving) RF-signals on a single or dual frequency band are well known for a long time. Antennas according to the state of the art including single band antennas demands generally a quite large amount of space, which make them unpractical for use where there is a need for small and efficient antenna means.

A quarter wave monopole 1A shown in figure 1a has a wide spread use due to its simplicity and good match for single band application where its height (generally written $\lambda/4$ which is 80-90 mm for 800-900 MHz) is acceptable. It is for car applications generally made of a metallic pin inside some more or less fancy designed plastic tube. A bigger diameter (or wider strip if made as a circuit board) will increase the bandwidth and external matching components can be used for the same purpose. The quarter wave monopole needs a ground plane which here is understood a rather big area of conducting material (having a diameter of one or more λ at the operating frequency of the antenna) which is a problem.

A so called L antenna 1B is shown in fig 1b. The main radiation in such a structure comes from the vertical part with respective

to a ground plane means 20 which by itself can be said to be a short monopole. The horizontal part is not radiating in proportion to its length but is rather a top loading to the vertical part. The top loading makes the radiating resistance up to 4 times higher than the monopole alone a fact which increases the bandwidth. Depending on the height of the vertical part the bandwidth can be sufficient for single band telephony in spite of a height in the order of $\lambda/8$. The band width will typically increase to the second or third power as a function of the height. Still multiband service is difficult to achieve and one obvious reason is that the total length is typically $\lambda/4$ which indicates drastically different matching conditions at twice the frequency when the height corresponds to $\lambda/2$ which is a problem.

The United States Patent US 5 629 712 discloses a vehicular radio reception antenna which is concealed within a body trim piece. Said antenna comprising a metal ground plane and a conducting loop connected to the ground plane at its first and second ends. Said loop circumscribes a slot area between the ground plane and the conducting loop. The length of the slot is selected to be $\lambda/2$ wavelength in the desired frequency band to be received by the antenna.

Since this kind of antenna is adapted to receive FM and/or AM signals said $\frac{1}{2}$ wavelength of the slot corresponds to about 1.5 meters which is a problem when the cubic capacity is scarce. Another problem is that said antenna is dependent on the shape of the car. Yet another problem is that said antenna requires external components such as capacitors or inductors for power compensation and frequency matching. Still another problem is that said antenna does not exhibit an omnidirectional radiating pattern.

The invention will now be described in more detail with reference to preferred embodiments thereof and also with reference to the accompanying drawings.

5 BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1a shows a development stage of an antenna device according to the state of the art.

10 Fig 1b shows a further development stage of an antenna device according to the state of the art.

Figure 2 shows a first embodiment of an antenna device according to the invention arranged on a ground plane means.

15 Figure 3 shows a second embodiment of an antenna device according to the invention arranged on a ground plane means.

20 Figure 4 shows a third embodiment of an antenna device according to the invention arranged on a ground plane means.

Figure 5 shows a fourth embodiment of an antenna device according to the invention arranged on a ground plane means.

25 Figure 6 shows a fifth embodiment of an antenna device according to the invention arranged on a ground plane means.

DESCRIPTION OF PREFERRED EMBODIMENTS

30 In this disclosure it is to be understood that the antenna system of the invention is operable to receive and/or transmit (transceive) radio signals. Even if a term is used herein that suggests one specific signal direction it is to be appreciated that such a situation can cover that signal direction and/or
35 its reverse.

Fig. 1a and 1b is described in connection with the prior art above.

5 With reference to Figure 2, a first embodiment of an antenna device 1 according to the invention is shown. The antenna device is arranged for transmission/reception of RF waves in at least one frequency band, e.g. in the 900 MHz band.

10 The antenna device 1 is to be connected to a radio communication device (not shown) arranged to a vehicle. As shown in the figures, the antenna device 1 is arranged on a ground plane means 20, such as a vehicle body. This ground plane means 20 will act as a ground plane. The ground plane
15 means 20 can be replaced by a conductive ground plane of proper size in a radio communication device, e.g. a PCB (printed circuit board).

The antenna device 1 comprises a conductive radiating structure
20 10 for transmission/reception of RF waves in said frequency band(s).

The conductive radiating structure 10, being in this embodiment essentially rectangular shaped, comprises a first end 12, a
25 second end 14, a tuning/matching means 16 and an bridge connector 18. A second elongated open loop (or internal elongated open loop) in said structure 10 is defined by the path from the first end to the second end via the bridge connector 18. A first elongated open loop (or an external
30 elongated open loop) is defined as a longest path from the first end to the second end in the conductive radiating structure 10. In Fig. 2 the tuning/matching means 16 is with a first side capacitively and inductively coupled to a second side of the bridge connector 18 and partly with a second side
35 capacitively and inductively coupled to a common side of the

rectangular shaped first and second elongated open loops located closest to the ground plane. Said bridge connector 18 having a first side capacitively and inductively coupled to a side of the first rectangular shaped elongated open loop located furthest away from the ground plane. The opening 17 of the first and second elongated open loop structures is in this embodiment located at a corner of the rectangle between the tuning/matching means 16 and the ground plane means 20. However, the opening 17 can be arranged somewhere along the common side of the first and second elongated open loops.

Due to the frequency dependence of the inductive coupling the second elongated open loop has a small influence to the lower frequency band but much higher to the higher frequency band. Thus a more efficient optimization is possible for two or multiband service.

The conductive radiating structure formed as an elongated open loop 10 is to be connected to a transmission/feed, for example a coaxial cable 19, at its second end 14, being in this embodiment a feed portion 15. The feed line is connected to transceiver circuits of a radio communication device.

The first end 12 of conductive radiating structure 10 is connected to ground. The distance between the first end 12 and the second end 14 along the second elongated open conductive radiating structure is in the range of $\lambda/4 - \lambda$, where λ is the wavelength of the desired frequency in the frequency band to be received/transmitted by the antenna. The first elongated open loop can be tuned to its desired frequency by adjusting said distance between the first and second ends 12, 14, by cutting at the second end 14 of the conductive radiating structure 10. The distance between the first end 12 and the second end 14 along the first elongated open loop is dependent on the choice of frequency band. If the second elongated loop is adjusted to

operate at a frequency at 1800 MHz and the first elongated loop is adjusted to receive a frequency at 900 MHz the relation between the distance between the first 12 and second ends of the first and second elongated loop is about 2:1.

The conductive radiating structure 10 is arranged on a ground plane means 20. The first end of the radiating structure is preferably capacitively connected to ground but can alternatively be galvanically connected to ground. If galvanically connected to ground said first end of the radiating structure can be provided with connection pins passing through holes in the ground plane means 20 acting as a ground plane or through holes in a metallic sheet acting as a ground plane. The pins are then preferably soldered to the ground plane means 20 or the metallic sheet.

The ground plane means 20 with a conductive portion of a proper size is sufficient for the antenna function, and the antenna device 1 can be mounted to a vehicle. However, if the antenna device 1 is mounted at a small height e.g. 0.5 mm above a vehicle roof or body, conductive portions of the vehicle are coupled, preferably capacitively, to the ground plane means 20. In this case said conductive portions also act as ground plane. However, the radiation of the antenna is dependent on the size of the ground plane.

The conductive radiating structure 10 is shown to be arranged orthogonal to the ground plane means 20. As mentioned above the first end of the conductive radiating structure is galvanically or capacitively coupled to the ground plane means 20. The second end of the conductive radiating structure is electrically isolated from the ground plane means 20. A transmission/feed line e.g. a coaxial cable 19 is with its electrical shielding connected to ground or directly to the first end of the radiating structure. A central conductor in

the coaxial cable 19 is connected to the second end of the conductive radiating structure.

The conductive radiating structure 10 is preferably
5 manufactured by stamping or cutting out the structure from a conductive plate e.g. metal plate. The width of the first and second elongated open loops in the conductive radiating structure 10 in the plane of the radiating structure is essentially larger than the thickness perpendicular to the
10 plane of the structure. Said radiating structure can be arranged to a dielectric substrate by means of rivets, screws, glue, tape or other equivalent means. Alternatively, said radiating structure could be made out of a electrical conductor having for example a round, rectangular or triangular cross
15 section. The structure could in a further alternative be formed on a dielectric carrier by printing or etching.

A surface defined by the conductive radiating structure is preferably orthogonal to the ground plane. However, said
20 surface of the structure can be arranged at an angle α with respect to said ground plane, where said angle α is in the range of 30-150°. Said surface of the structure is preferably plane but can be curved or folded in a C-shaped or V-shaped manner respectively.

25 The direction of polarisation is orthogonal to the ground plane. The loop structure 10 radiates the desired frequency in a omnidirectional pattern.

30 With reference to Figure 3, a second embodiment of an antenna device 1 according to the invention is shown. The antenna device is arranged for transmission/reception of RF waves in at least one frequency band, e.g. in the 900 MHz band.

The antenna device 1 is to be connected to a radio communication device (not shown) arranged to a vehicle. As shown in figure 3, the antenna device 1 is arranged on a ground plane means 20. The ground plane means 20 could be a conductive ground plane of proper size in a radio communication device, e.g. a PCB (printed circuit board).

The antenna device 1 comprises a conductive radiating structure formed as an elongated open loop 10 for transmission/reception of RF waves in said frequency band(s).

The conductive radiating structure formed as an elongated open loop 10, being in this embodiment essentially rectangular shaped, comprises a first end 12 and a second end 14. Said conductive radiating structure formed as an elongated open loop further comprises tuning/matching means 16, 17. Said tuning/matching means being elements for tuning the radiating structure to the desired operating frequencies by the antenna. In this embodiment the tuning/matching means 16 is with a first side capacitively and inductively coupled to a side of the rectangular shaped elongated open loop structure being located furthest away from the ground plane means 20 and partly with a second side to a open portion (17) of said elongated open loop structure being located closest to the ground plane means 20.

The conductive radiating structure formed as an elongated open loop 10 is to be connected to a transmission/feed, for example a coaxial cable 19, at its second end 14 being in this embodiment a feed portion 15. The feed line is connected to transceiver circuits of a radio communication device.

The first end 12 of the conductive radiating structure formed as an elongated open loop 10 is connected to ground. The distance between the first end 12 and the second end 14 along the conductive radiating structure formed as an elongated open

loop is in the range of $\lambda/4$ - λ , where λ is the wavelength of the desired frequency in the frequency band to be received/transmitted by the antenna. The conductive radiating structure formed as an elongated open loop 10 can be tuned to its frequency by adjusting said distance between its the first and second ends 12, 14, by cutting at the second end 14 of the conductive radiating structure formed as an elongated open loop 10.

The conductive radiating structure formed as an elongated open loop 10 is arranged on a ground plane means 20. The first end 12 of the conductive radiating structure formed as an elongated open loop 10 is preferably capacitively connected to ground but can alternatively be galvanically connected to ground. If galvanically connected to ground said first end of the conductive radiating structure formed as an elongated open loop can be provided with connection pins passing through holes in the ground plane means 20 acting as a ground plane or through holes in a metallic sheet acting as a ground plane. The pins are then preferably soldered to the ground plane means 20 or the metallic sheet.

The ground plane means 20 with a conductive portion of a proper size is sufficient for the antenna function, and the antenna device 1 can be mounted to a vehicle. However, if the antenna device 1 is mounted at a small height e.g. 0.5 mm above a vehicle roof or body, conductive portions of the vehicle are coupled, preferably capacitively, to the ground plane means 20. In this case said conductive portions also act as ground plane. However, the radiation of the antenna is dependent on the size of the ground plane.

The conductive radiating structure formed as an elongated open loop 10 is shown to be arranged orthogonal to the ground plane means 20. As mentioned above the first end of the conductive

radiating structure formed as an elongated open loop is capacitively or galvanically coupled to the ground plane means 20. The second end of the conductive radiating structure formed as an elongated open loop is electrically isolated from the ground plane means 20, i.e. ground. A transmission/feed line e.g. a coaxial cable 19 is with its electrical shielding connected to ground or directly to the first end of the conductive radiating structure formed as an elongated open loop. A central conductor in the coaxial cable 19 is connected to the second end of the conductive radiating structure formed as an elongated open loop.

The conductive radiating structure formed as an elongated open loop 10 is preferably manufactured by stamping or cutting out the structure from a conductive plate e.g. metal plate, i.e. manufactured in one piece. The width of the conductive radiating structure formed as an elongated open loop in the plane of the radiating structure is essentially larger than the thickness perpendicular to the plane of the structure. Said radiating structure can be arranged to a dielectric substrate by means of rivets, glue, screws, tape or other equivalent means.

A surface defined by the conductive radiating structure 10 formed as an elongated open loop is preferably orthogonal to the ground plane. However, said surface of the conductive radiating structure formed as an elongated open loop can be arranged at an angle α with respect to said ground plane, where said angle α is in the range of 30-150°. Said surface of the conductive radiating structure formed as an elongated open loop is preferably a plane surface but can be curved or folded in a C-shaped or V-shaped manner respectively.

The direction of polarisation is orthogonal to the ground plane. The conductive radiating structure formed as an

elongated open loop 10 radiates the desired frequency in a omnidirectional pattern.

With reference to Figure 4, a third embodiment of an antenna device 1 according to the invention is shown. The antenna device is arranged for transmission/reception of RF waves in at least one frequency band, e.g. in the 900 MHz band.

The antenna device 1 is to be connected to a radio communication device (not shown) arranged to a vehicle. As shown in the figure, the antenna device 1 is arranged on a ground plane means 20, such as a vehicle body. This ground plane means 20 will act as a ground plane. The ground plane means 20 can be replaced by a conductive ground plane of proper size in a radio communication device, e.g. a PCB (printed circuit board). The radiation from the antenna device is dependent on the size of the ground plane.

The antenna device 1 comprises a conductive radiating structure 10 formed as an elongated open loop (EOLA) for transmission/reception of RF waves in said frequency band(s).

The conductive radiating structure 10, being in this embodiment essentially meander shaped, comprises a first end 12 and a second end 14. The conductive radiating structure can be seen as derived from an L antenna with a second vertical part added and also a horizontal bottom part. The last horizontal part is radiating very little due to its position close to the ground plane. Its important mission however is to be a kind of low reactive impedance load (as compared to an open end) to the second vertical part in order to enable a second vertical current. Furthermore it is possible to chose parameters to give said reactive impedance a size appropriate for adjusting the phase of said current so that the current in the two vertical

parts are co-operating in order to increase bandwidth and make the radiation omnidirectional.

In some applications (like a car or a boat with a plastic roof) a very small ground plane can be used and the flexibility of the radiating structure formed as an elongated open loop allows the tuning of the antenna to the small ground plane in spite of the difference of the impedance conditions. The small ground plane is here defined as a plane having a radius being less than λ at the desired operating frequency by the antenna.

The conductive radiating structure 10 is to be connected to a feed line, which could be any type of transmission/feed line, at its second end 14. The feed line is connected to transceiver circuits of a radio communication device.

The first end 12 of the conductive radiating structure 10 is connected to ground of the radio communication device. The distance between the first end 12 and the second end 14 along the conductive radiating structure 10 is in the range of $\lambda/4 - \lambda$, where λ is the wavelength of the desired frequency in the frequency band(s) to be received/transmitted by the antenna. The conductive radiating structure can be tuned to its frequency by adjusting said distance between its the first and second ends 12, 14, by cutting at the second end 14 of the conductive radiating structure 10.

The conductive radiating structure 10 is arranged on a ground plane means 20. The first end of the loop structure is preferably galvanically connected to ground but can alternatively be capacitively connected to ground. If galvanically connected to ground said first end of the radiating structure can be provided with connection pins passing through holes in the ground plane means 20 acting as a ground plane or through holes in a metallic sheet acting as a

ground plane. The pins are then preferably soldered to the ground plane means 20 or the metallic sheet.

5 The ground plane means 20 includes a substrate with a conductive portion of a proper size is sufficient for the antenna function, and the antenna device 1 can be mounted to a vehicle. However, if the antenna device 1 is mounted at a small height e.g. 0.5 mm above a vehicle roof or body, conductive portions of the vehicle are coupled, capacitively, to the
10 conductive portion of the ground plane means 20. In this case said conductive portions also act as ground plane. The radiation of the antenna is however dependent on the size of the ground plane.

15 The conductive radiating structure formed as an elongated open loop 10 is shown to be arranged orthogonal to the ground plane means 20. As mentioned above the first end of the conductive radiating structure formed as an elongated open loop is galvanically or capacitively coupled to the ground plane means
20 20. The second end 14 of the conductive radiating structure formed as an elongated open loop is electrically isolated from the ground plane means 20. A transmission line/feed line e.g. a coaxial cable 19 is with its electrical shielding connected to ground or directly to the first end of the conductive radiating
25 structure formed as an elongated open loop 10. A central conductor 15 in the coaxial cable 19 is connected to the second end 14 of the conductive radiating structure formed as an elongated open loop 10. Said second end being in thus embodiment a feed portion.

30 The conductive radiating structure formed as an elongated open loop 10 is preferably manufactured by stamping or cutting out the structure from a conductive plate e.g. metal plate. The width of the conductive radiating structure formed as an
35 elongated open loop in the plane of the radiating structure is

essentially larger than the thickness perpendicular to the plane of the structure. Said conductive radiating structure formed as an elongated open loop can be arranged on a carrier in the form of a dielectric substrate. Alternatively, said
5 radiating structure could be made out of an electrical conductor having for example a round, rectangular or triangular cross section. The structure could in a further alternative be formed on a dielectric carrier by printing or etching.

10 A surface defined by the conductive radiating structure formed as an elongated open loop 10 is preferably orthogonal to the ground plane means 20. However, said surface of the conductive radiating structure formed as an elongated open loop 10 can be arranged at an angle α with respect to said ground plane,
15 where said angle α is in the range of 30-150°. Said surface of the conductive radiating structure formed as an elongated open loop 10 is preferably a plane surface but can be curved or folded in a C-shaped or V-shaped manner respectively.

20 The direction of polarisation is orthogonal to the ground plane means 20. The conductive radiating structure formed as an elongated open loop 10 radiates the desired frequency in a omnidirectional pattern.

25 With reference to Figure 5, a fourth embodiment of an antenna device 1 according to the invention is shown. The antenna device is arranged for transmission/reception of RF waves in at least one frequency band, e.g. in the 900 MHz band.

30 The antenna device 1 is to be connected to a radio communication device (not shown) arranged to a vehicle. As shown in the figures, the antenna device 1 is arranged on a ground plane means 20, such as a vehicle body. This ground plane means 20 will act as a ground plane. The ground plane
35 means 20 can be replaced by a conductive ground plane of proper

The antenna device 1 comprises a conductive radiating structure 10 for transmission/reception of RF waves in said frequency band(s).

Due to the frequency dependence of the inductive coupling the second elongated open loop has a small influence to the lower frequency band but much higher to the higher frequency band.

Thus a more efficient optimization is possible for two or multiband service.

In figure 5 the tuning/matching means 16 is with a first side capacitively and inductively coupled to a side of the rectangular shaped radiating structure 10 located perpendicular to the ground plane means 20. The tuning/matching means is introduced to optimize performance in the highest band only. In this embodiment said tuning/matching means can be seen as an extra mono pole. Said bridge connector 18 having a first side capacitively and inductively coupled to a side of the first rectangular shaped elongated open loop located furthest away from the ground plane. Said bridge connection having parts of a second side capacitively and inductively coupled to an open portion 17 of the common side of the rectangular shaped first and second elongated open loops located closest to the ground plane. The opening portion 17 of the first and second elongated open loops is in this embodiment located in a middle of the common side of said rectangular shaped loops being located closest to the ground plane.

The conductive radiating structure formed as a first and second elongated open loops 10 is to be connected to a transmission/feed line. The transmission line/feed line that could be a coaxial cable 19 is with its central conductor 15 feeding the radiating structure at the second end being a feed portion. The transmission/feed line is connected to transceiver circuits of a radio communication device.

The first end 12 of conductive radiating structure 10 is connected to ground. The distance between the first end 12 and the second end 14 along the second elongated open conductive radiating structure is in the range of $\lambda/4 - \lambda$, where λ is the wavelength of the desired frequency in the frequency band to be received/transmitted by the antenna. The first elongated open loop can be tuned to its desired frequency by adjusting said

distance between the first and second ends 12, 14, by cutting at the second end 14 of the conductive radiating structure 10. The distance between the first end 12 and the second end 14 along the first elongated open loop is dependent on the choice of frequency band. If the second elongated loop is adjusted to operate at a frequency at 1800 MHz and the first elongated loop is adjusted to receive a frequency at 900 MHz the relation between the distance between the first 12 and second ends of the first and second elongated loop is about 2:1.

The conductive radiating structure 10 is arranged on a ground plane means 20. The first end of the radiating structure is preferably capacitively connected to ground but can alternatively be galvanically connected to ground. If galvanically connected to ground said first end of the radiating structure can be provided with connection pins passing through holes in the ground plane means 20 acting as a ground plane or through holes in a metallic sheet acting as a ground plane. The pins are then preferably soldered to the ground plane means 20 or the metallic sheet.

The ground plane means 20 with a conductive portion of a proper size is sufficient for the antenna function, and the antenna device 1 can be mounted to a vehicle. However, if the antenna device 1 is mounted at a small height e.g. 0.5 mm above a vehicle roof or body, conductive portions of the vehicle are coupled, preferably capacitively, to the ground plane means 20. In this case said conductive portions also act as ground plane. However, the radiation of the antenna is dependent on the size of the ground plane.

The conductive radiating structure 10 is shown to be arranged orthogonal to the ground plane means 20. As mentioned above the first end of the conductive radiating structure is galvanically or capacitively coupled to the ground plane means 20. The

second end of the conductive radiating structure is electrically isolated from the ground plane means 20. A transmission/feed line e.g. a coaxial cable 19 is with its electrical shielding connected to ground or directly to the first end of the radiating structure. A central conductor in the 19 cable is connected to the second end of the conductive radiating structure.

The conductive radiating structure 10 is preferably manufactured by stamping or cutting out the structure from a conductive plate e.g. metal plate. The width of the first and second elongated open loops in the conductive radiating structure 10 in the plane of the radiating structure is essentially larger than the thickness perpendicular to the plane of the structure. Said radiating structure can be arranged to a dielectric substrate by means of rivets, screws, glue, tape or other equivalent means. Alternatively, said radiating structure could be made out of a electrical conductor having for example a round, rectangular or triangular cross section. The structure could in a further alternative be formed on a dielectric carrier by printing or etching.

A surface defined by the conductive radiating structure is preferably orthogonal to the ground plane. However, said surface of the structure can be arranged at an angle α with respect to said ground plane, where said angle α is in the range of 30-150°. Said surface of the structure is preferably plane but can be curved or folded in a C-shaped or V-shaped manner respectively.

The direction of polarisation is orthogonal to the ground plane. The loop structure 10 radiates the desired frequency in a omnidirectional pattern.

In the previous embodiments the antenna means has been provided with a ground plane means 20. When mounted on a vehicle, this ground plane means 20 can be coupled to conductive portions of the vehicle galvanically and/or capacitively. Alternatively the ground plane means 20 can be omitted and the conductive portions of the vehicle act as ground plane means.

CLAIMS

1. An antenna means for transmitting and/or receiving RF signals in at least a first frequency band, comprising:

- 5 - a ground plane means (20) arranged to be connected to ground of a circuitry of a radio communication device,
- a conductive radiating structure (10) having a first end (12) and a second end (14),
- 10 - said conductive radiating structure (10) is arranged separated from the ground plane means (20), characterised in that
- said conductive radiating structure is formed as at least a first elongated open loop,
- said first end (12) is arranged to be connected to
15 ground of said radio communication device, and
- a feed portion is arranged in vicinity of the first and/or second ends.

2. The antenna means according to claim 1, characterised in that said second end being a feed portion.

20 3. The antenna means according to claim 1 or 2, characterised in that said conductive radiating structure (10) having a total length of $\lambda/4$ - λ at a frequency in the frequency band to be received and/or transmitted by the antenna.

25 4. The antenna means according to any of the claims 1-3, characterised in that said conductive radiating structure (10) being a flexible film attached to a dielectric substrate.

5 5. The antenna means according to any of the claims 1-4, characterised in that said conductive radiating structure (10) exhibits at least a planar section, said planar section is forming an angle (α) with said ground plane means, where (α) is in the range of 30-150°.

6. The antenna means according to claim 5, characterised in that a surface of said conductive radiating structure (10) being curved or folded such as to include C-shapes or V-shapes.

10 7. The antenna means according to any of the preceding claims, characterised in that said conductive radiating structure (10) being meander shaped.

15 8. The antenna means according to any of the preceding claims, characterised in that it further comprises a tuning/matching means (16) for tuning/matching to one or multiple frequencies.

20 9. The antenna means according to claim 8, characterised in that said tuning/matching means (16) is an electrical conductor having a first end and a second end, where said first end being arranged to said at least one elongated open loop, said second end being a free end and at least a part of at least one side of said conductor is capacitively coupled to said at least one elongated open loop.

25 10. The antenna means according to claim 9, characterised in that said electrical conductor (16) being meander shaped.

30 11. The antenna means according to any of the preceding claims, characterised in that it further comprises at least one bridge connector (18) being an electrical conductor with a first end and a second end, each connected to different parts of said at least one elongated open loop.

16. An antenna assembly including an antenna means (1) according to any preceding claim, wherein the assembly comprises at least one further antenna element for transmitting/receiving radio frequency signals, for instance, a GPS antenna.

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
12 April 2001 (12.04.2001)

PCT

(10) International Publication Number
WO 01/26182 A1

(51) International Patent Classification⁷: H01Q 1/38, 1/32

(21) International Application Number: PCT/SE00/01933

(22) International Filing Date: 4 October 2000 (04.10.2000)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
9903573-5 4 October 1999 (04.10.1999) SE

(71) Applicant (for all designated States except US):
SMARTEQ WIRELESS AB [SE/SE]; Box 4064,
S-182 04 Enebyberg (SE).

(72) Inventors; and

(75) Inventors/Applicants (for US only): HELLGREN, Mat-
tias [SE/SE]; Gribbylundsvägen 60, S-187 65 Täby (SE).
CARLSSON, Lars [SE/SE]; Svärslångsvägen 39, S-120
60 Årsta (SE).

(74) Agents: ASKERBERG, Fredrik et al.; L.A. Groth & Co.
KB, Box 6107, S-102 32 Stockholm (SE).

(81) Designated States (*national*): AE, AG, AL, AM, AT, AT
(utility model), AU, AZ, BA, BB, BG, BR, BY, BZ, CA,
CH, CN, CR, CU, CZ, CZ (utility model), DE, DE (utility
model), DK, DK (utility model), DM, DZ, EE, EE (utility
model), ES, FI, FI (utility model), GB, GD, GE, GH, GM,
HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK,
LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX,
MZ, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SK
(utility model), SL, TJ, TM, TR, TT, TZ, UA, UG, US, UZ,
VN, YU, ZA, ZW.


(84) Designated States (*regional*): ARIPO patent (GH, GM,
KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZW), Eurasian
patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European
patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE,
IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG,
CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).

Published:

— With international search report.

For two-letter codes and other abbreviations, refer to the "Guid-
ance Notes on Codes and Abbreviations" appearing at the begin-
ning of each regular issue of the PCT Gazette.

(54) Title: ANTENNA MEANS



(57) Abstract: The present invention relates to an antenna means for transmitting and/or receiving RF-signals in at least a first fre-
quency band. The antenna means comprising a ground plane means (20) arranged to be connected to ground of a circuitry of a radio
communication device, a conductive radiating structure (10) having a first end (12) and a second end (14), where said conductive
radiating structure (10) being separated from the ground plane means (20). Said first end (12) being connected to ground and said
second end (14) being a feed portion.

WO 01/26182 A1




Fig. 1a




Fig. 1b




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6

DECLARATION AND POWER OF ATTORNEY U.S.A.

ATTORNEYS' DOCKET NO.

ALL PATENTS, INCLUDING DESIGN
FOR APPLICATION BASED ON PCT, PARIS CONVENTION,
PRIORITY FOR PROVISIONAL APPLICATIONS

As a below named inventor, I declare that my residence, post office address and citizenship are stated below next to my name, the information given herein is true, that I believe that I am the original, first and sole inventor (if only one name is listed at 201 below), or an original, first and joint inventor (if plural inventors are named below at 201-203, or on additional sheets attached hereto) of the subject matter which is claimed and for which patent is sought on the invention entitled:

ANENNA MEANS

which is described and claimed in:

☒ PCT International Application No.

SE00/01933

filed

4 October 2000

☐ the attached specification

☐ the specification in application Serial No.

filed

(if applicable) and amended on

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, §1.56.

I hereby claim foreign priority benefits under Title 35, United States Code, §119 (a)-(d) of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed:

Prior Foreign Application(s)

9903573-5

Sweden

04 Oct. 1999

(Number)

(Country)

(Day/Month/Year Filed)

Priority Claimed

☒ Yes

☐ No

(Number)

(Country)

(Day/Month/Year Filed)

☐ Yes

☐ No

(Number)

(Country)

(Day/Month/Year Filed)

☐ Yes

☐ No

I hereby claim the benefit under Title 35, United States Code, §119(e) of any United States provisional application(s) listed below:

Application No.

Filing Date

Application No.

Filing Date

I hereby claim the benefit under Title 35, United States Code, §120 of any United States application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States Code, §112, I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, §1.56 which became available between the filing date of the prior application and the national or PCT International filing date of this application:

(Application Serial No.)

(Filing Date)

(Status: patented, pending, abandoned)

POWER OF ATTORNEY: As a named inventor, I hereby appoint the following attorneys (Registration No.) to prosecute this application, receive and act on instructions from my agent, and transact all business in the Patent and Trademark Office connected therewith. HARVEY B. JACOBSON, JR. (20,851); JOHN CLARKE HOLMAN (22,769); MARVIN R. STERN (20,640); ALLEN S. MELSER (27,215); MICHAEL R. SLOBASKY (26,421); JONATHAN L. SCHERER (29,851); IRWIN M. AISENBERG (19,007); WILLIAM E. PLAYER (31,409); YOON S. HAM (45,307) and NATHANIEL A. HUMPHRIES (22,772)

SEND CORRESPONDENCE TO: CUSTOMER NO. 00136

or

JACOBSON HOLMAN
PROFESSIONAL LIMITED LIABILITY COMPANY
400 SEVENTH STREET, N.W.
WASHINGTON, D.C. 20004

DIRECT TELEPHONE CALLS TO:

(please use Attorney's Docket No.) (202) 638-6666

JACOBSON HOLMAN

PROFESSIONAL LIMITED LIABILITY COMPANY

*Inventor(s) name must include at least one unabbreviated first or middle name.

201	FULL NAME * OF INVENTOR	FAMILY NAME HELLGREN	GIVEN NAME Mattias	MIDDLE NAME
	RESIDENCE & CITIZENSHIP	CITY TÄBY	STATE OR FOREIGN COUNTRY Sweden	COUNTRY OF CITIZENSHIP Sweden
	POST OFFICE ADDRESS	POST OFFICE ADDRESS Gribblylundsvägen 60	CITY 5-187 65 TÄBY	STATE OR COUNTRY Sweden
202	FULL NAME * OF INVENTOR	FAMILY NAME CARLSSON	GIVEN NAME Lars	MIDDLE NAME
	RESIDENCE & CITIZENSHIP	CITY ÄRSTA	STATE OR FOREIGN COUNTRY Sweden	COUNTRY OF CITIZENSHIP Sweden
	POST OFFICE ADDRESS	POST OFFICE ADDRESS Svärdslångsvägen 39	CITY 5-120 60 ÄRSTA	STATE OR COUNTRY Sweden
203	FULL NAME * OF INVENTOR	FAMILY NAME	GIVEN NAME	MIDDLE NAME
	RESIDENCE & CITIZENSHIP	CITY	STATE OR FOREIGN COUNTRY	COUNTRY OF CITIZENSHIP
	POST OFFICE ADDRESS	POST OFFICE ADDRESS	CITY	STATE OR COUNTRY ZIP CODE

I further declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment or both, under section 1001 of Title 18 of the United States Code; and that such willful false statements may jeopardize the validity of the application or any patent issuing thereon.

SIGNATURE OF INVENTOR 201*	SIGNATURE OF INVENTOR 202*	SIGNATURE OF INVENTOR 203*
DATE 26/2-01	DATE 020507	DATE

☐ Additional inventors are named on separately numbered sheets attached hereto.